


SA3218




Dimension(W×H×D):988×520×714mm

PRODUCT PROFILE


3 low-pass filters (80Hz, 100Hz, 120Hz) in SA3218 are available to choose according to different venues and music styles. There is also phase switch. All connectors and function buttons are on the back panel.

SA3218 subwoofer is with 1-way XLR for input and output. Signals can be sent to different speakers for sound distribution.


ACCESSORIES FOR SA3218




Flightcase
For 1 cabinet,
with 100mm wheels



Rain bag
(customized)



Wheel



Dolly
(customized)

SPECIFICATION

Type	Active DSP-controlled Compact Subwoofer
Frequency Response (-6dB anechoic chamber)	35Hz-150Hz
Maximum Calculated SPL/1M (Continuous/Peak)	134dB/140dB
LF Driver	Customized driver, 4"voice coil
AMPLIFIER	
Amplifier Circuitry	Class D
Power (Peak)	4000W
Frequency Response (1W 8Ω 2ch)	20Hz-20KHz(±0.5dB)
Intermodulation Distortion	<0.05%
Total Harmonic Distortion	<0.05%
Protection	DC protection, short circuit protection, overheat protection, input overload protection, output overload protection, soft startup protection, overvoltage protection, undervoltage protection
Cooling System	Cooling with fans, air convection
DSP	
Processor	96KHz signal sampling frequency, 24bit precision
Presets	80Hz, 100Hz, 120Hz
Crossover	Controlled by DSP
Output/Input	
Signal Input	1× female XLR
Signal Output	1× male XLR
Power Input	3 pin plug
AC Power Operating Range	100V~130V or 220V~240V (±10%, 50/60Hz)
Cabinet	
Cabinet Material	CNC made of excellent wood
Cabinet Color	Black is standard and default color. Consult with Audiocenter sales team for other customized colors
Pole Mount	M20 base Φ35mm
Dimension (W×H×D)	988x520x714mm
Net Weight	70.0Kg

SUGGESTED APPLICATION



Multi-functional meeting room



Museum



DJ



Wedding

SYSTEM CONFIGURATION

- SA3 full range loudspeaker or the same type of full range loudspeaker